

F7-USB Datasheet

F7-USB 7-Input Compact Stereo Mixer With Effects



Commercial

Product code	F7-USB
Price	USD 29.00 per piece
Minimum order quantity	100 pieces
Availability	In Stock
Manufacturer	Enping Weymic Electronic Technology Co., Ltd

Overview

The F7-USB is the model that does the most for the least. Seven inputs cover a small band or a presentation rig, effects are on board, and unlike most desks at this price the specification is published: 20 Hz to 25 kHz within +/-1 dB, 0 to +40 dB of microphone gain, 120 dB E.I.N., and three EQ bands at defined centre frequencies. At 29 USD with a hundred-piece minimum it is the obvious volume line for a distributor who still wants numbers on the box.

Technical Specification

Mic input	Electronically balanced, discrete input configuration
Mic frequency response	20 Hz to 25 kHz, +/-1 dB
Mic gain range	0 dB to +40 dB
Mic signal to noise	120 dB E.I.N.
Line input	Electronically balanced
Line frequency response	20 Hz to 25 kHz, +/-1 dB

Line gain range	-20 dB to +20 dB
Line signal to noise	95 dB
Stereo channel response	20 Hz to 25 kHz, +/-1 dB
Stereo gain range	Line -20 dB to +10 dB
Stereo signal to noise	Line 95 dB
EQ low	80 Hz, +/-15 dB
EQ mid	2500 Hz, +/-15 dB
EQ high	12 kHz, +/-15 dB

All figures above are published by the factory on the F7-USB product listing.

Features

1	Seven inputs
2	48V phantom power
3	On-board effects
4	USB connectivity
5	Three-band EQ at 80 Hz, 2500 Hz and 12 kHz
6	Electronically balanced mic and line inputs

Applications

Small live venues and bars · School and community hall PA · Rehearsal rooms · Home and project studios · Portable presentation rigs

Values shown as TBC are not published by the factory and are available on request. Prices are per piece and exclude shipping. Specifications are subject to change.